

Wafadrive command summary

COMMAND	FUNCTION
NEW	Clears OS and program
NEW#	Clears BASIC but leaves OS
NEW*	Initialises OS.
LOAD*	Load first program.
LOAD*"n:file"	Loads specified file (n is optional)
LOAD*"n:file", start, length	Load machine code.
SAVE*"n:file"	Save file
SAVE*"n:file"LINE s	Save BASIC with autorun
SAVE*"n:file", st, len, runadd	Save code with autorun.
SAVE#	Save with replace, use above parameters
VERIFY*"n:file"	Verify program/machine code
MERGE*"n:file"	Merge Basic
ERASE*"n:file"	Erase
MOVE*"n:file1" TO "n:file2"	Copy file1 TO file2
CAT#"n:"	Set default drive eg CAT # "a:"
CAT*"n:"	Display directory (from Ram).
FORMAT*"n:name"	Format wafer
FORMAT*"R";baud	Set baud rate (default 1200)
OPEN#*stream;channel	Open stream to channel
CLOSE#*stream	Close stream
CLEAR*	Close all streams
CLS*	Set screen to default colours.

No network and drives are always a: or b: (a: default),
default becomes last drive accessed.

So NEW* followed by CAT*"a:" should catalog your drive A.